See all 168 Products in Family

794.7nm CWL, 50mm Dia.,High Transmission Traditional Coated 10nm Bandpass Filter

High Transmission Traditional Coated Bandpass Filters

Stock **#71-722** **1 In Stock**

- 1 + **£440**.00

ADD TO CART

Volume Pricing	
Qty 1-10	**£440.00** each
Qty 11-25	**£374.00** each
Need More?	Request Quote

Prices shown are exclusive of VAT/local taxes

Product Downloads

General

Type:

Bandpass Filter

Physical & Mechanical Properties

Diameter (mm):

50.00 +0/-0.25

Clear Aperture CA (mm):

45.0

Thickness (mm):
5.90

Construction:
Mounted in Black Anodized Ring

Optical Properties

Center Wavelength CWL (nm):
794.70

Center Wavelength CWL Tolerance (nm):
+2/-0

Full Width-Half Max FWHM (nm):
10.00

Full Width-Half Max FWHM Tolerance (nm):
±2

Minimum Transmission (%):
80

Coating:
Traditional Coated

Blocking Wavelength Range (nm):
$1x10^{-4}$ avg. X-Ray to 1200nm

Environmental & Durability Factors

Operating Temperature (°C):
-50 to +70

Regulatory Compliance

RoHS 2015:
Compliant

Certificate of Conformance:
View

REACH 241:
Compliant

Product Details

- Passband Transmission up to 80%
- 441.6 to 1064nm Wavelength Options with 10, 20, and 40nm Bandwidths
- Ideal for Medical and Analytical Applications

High Transmission Traditional Coated Bandpass Filters are designed for situations where far-infrared blocking is not required, allowing for up to 80% transmission in the passband region and good blocking over the visible and NIR wavelength range. Featuring popular laser, mercury, biomedical, and analytical spectral lines, these filters cover a wide range of visible and NIR wavelengths. A hermetic seal and an anodized metal mount help maintain performance in high humidity environments and protect against chipping and scratching. High Transmission Traditional Coated Bandpass Filters are ideal for a range of scientific and medical applications such as spectral radiometry, medical diagnostics, chemical analysis, and Colorimetry. For applications requiring wider blocking ranges, **traditional coated bandpass filters** are available whereas applications requiring higher transmission above 90% are best served with **hard coated bandpass filters**.

;